Dual 2-Input NAND Gate

The NL27WZ00 is a high performance dual 2–input NAND Gate operating from a 1.65 V to 5.5 V supply.

- Extremely High Speed: t_{PD} 2.4 ns (typical) at $V_{CC} = 5 V$
- Designed for 1.65 V to 5.5 V V_{CC} Operation
- Over Voltage Tolerant Inputs
- LVTTL Compatible Interface Capability With 5 V TTL Logic with V_{CC} = 3 V
- LVCMOS Compatible
- 24 mA Balanced Output Sink and Source Capability
- Near Zero Static Supply Current Substantially Reduces System Power Requirements
- Replacement for NC7WZ00
- Chip Complexity: FET = 112



Figure 1. Pinout

PIN ASSIGNMENT

Pin	Function		
1	A1		
2	B1		
3	Y2		
4	GND		
5	A2		
6	B2		
7	Y1		
8	V _{CC}		



ON Semiconductor®

http://onsemi.com

MARKING DIAGRAM



D = Date Code

ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 4 of this data sheet.



Figure 2. Logic Symbol

FUNCTION TABLE

I = AD					
Inputs		Output			
Α	В	Y			
L	L	Н			
L	Н	Н			
Н	L	Н			
Н	н	L			

H = HIGH Logic Level

L = LOW Logic Level

© Semiconductor Components Industries, LLC, 2003 November, 2003 – Rev. 4





Figure 3. Switching Waveform



DEVICE ORDERING INFORMATION

	Device Nomenclature							
Device Order Number	Logic Circuit Indicator	No. of Gates per Package	Temp Range Identifier	Technology	Device Function	Package Suffix	Package Type	Tape and Reel Size [†]
NL27WZ00US	NL	2	7	WZ	00	US	US8	178 mm, 3000 Unit

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.



Figure 5. Tape Ends for Finished Goods



Figure 6. US8 Reel Configuration/Orientation





REEL DIMENSIONS

Tape Size	T and R Suffix	A Max	G	t Max
8 mm	US	178 mm (7 in)	8.4 mm, + 1.5 mm, –0.0 (0.33 in + 0.059 in, –0.00)	14.4 mm (0.56 in)





PACKAGE DIMENSIONS

US8 **US SUFFIX** CASE 493-02 **ISSUE A**



6 °

10 °

http://onsemi.com 7

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters witch with event to subtain life, or for any other application in which the failure of the SCILLC product sate sheets and/or specifications can and to even yin different applications inplant into the body, or other applications intended to support or sustain life, or for any other application in which the SCILLC product caude treate a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use pay stat as and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800–282–9855 Toll Free USA/Canada

Japan: ON Semiconductor, Japan Customer Focus Center 2–9–1 Kamimeguro, Meguro–ku, Tokyo, Japan 153–0051 Phone: 81–3–5773–3850 ON Semiconductor Website: http://onsemi.com

Order Literature: http://www.onsemi.com/litorder

For additional information, please contact your local Sales Representative.